

# marantz®



## SR7013

### 9.2 CHANNEL NETWORK AV RECEIVER WITH UNIQUE AURO-3D AND IMAX ENHANCED




Enjoy three-dimensional audio and advanced video processing with the 9.2 channel Marantz SR7013. For superior music quality, Marantz-unique HDAM circuit technology provides optimal fidelity and dynamic range of high-resolution files. Stream music from Spotify, TIDAL, Deezer, Amazon Music and more with built-in Bluetooth, HEOS or AirPlay 2, and control it all with Amazon Alexa voice compatibility.

#### Highlights

#### Your Benefits

9.2 channel AV Receiver with 200W per channel; 11.2ch processing	Enough power to fill big rooms with renowned Marantz sound
Dolby Atmos and DTS:X (up to 7.1.4 with external 2ch amplifier), Auro-3D	Immersive 3D sound with effects from overhead
IMAX Enhanced audio decoding (update)	Offers a new level of quality in immersive sight and sound experiences
Marantz sound tuning with all-new components, including current feedback HDAM pre-amplifier section	Designed for purity with both movies and music for all-round entertainment capability
High performance AKM AK4458 192kHz/32bit D/A converters for all channels	Highest resolution for music and movie sound
Audyssey MultEQ XT32, LFC, Sub EQ HT, Dynamic Volume and Dynamic EQ	Delivering the ultimate equalization for your individual room
Built-in WiFi with 2.4GHz/5GHz dual band support	Improved network stability especially in WiFi-crowded environments
AirPlay, Bluetooth, Internet Radio, Spotify Connect, TIDAL, Deezer	Access to almost unlimited online music sources
Network Streaming: DSD (2.8/5.6MHz), FLAC, ALAC and WAV support	High Resolution audio streaming for HiFi enthusiasts
HEOS Music Streaming Technology and the HEOS App	Comfortable control of music sources, and multi-room experience with other HEOS products
4K/60 Hz, 4:4:4, HDR and BT.2020, Dolby Vision compatible, HLG	Latest HDMI standard for future-proof compatibility
8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support; 3 HDMI outputs (zone)	Plenty of inputs for your digital devices; different video in different rooms
eARC (Enhanced Audio Return Channel)	Allows 3D audio transmission from TV via HDMI audio return channel
Colour-coded speaker terminals, Setup Assistant, Marantz AVR Remote App	Hassle-free installation, setup and operation
Advanced Multi-Room options; 11.2ch Pre-out; RS232 Control; Crestron Connected, IP-control	Audio and video in multiple rooms; ready for 3rd Party Home Automation systems



# because music matters

## SR7013

## 9.2 CHANNEL NETWORK AV RECEIVER WITH UNIQUE AURO-3D AND IMAX ENHANCED



Design and specifications are subject to change by Marantz without notice.

FEATURES	SR7013
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Auro-3D / Auromatic	• / •
Multichannel Stereo	•
IMAX Enhanced	•
Compressed audio Enhancer: MDAX2	•
Audyssey	MultEQ XT32 with LFC/Sub EQ HT
Audyssey Dynamic EQ / Dynamic Volume	• / •
Audyssey MultEQ Editor App support	•
<b>NETWORK / SOURCES</b>	
Network Audio Streaming	•
HEOS Multiroom integrated	•
Works with Amazon Alexa	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay 2 audio streaming	•
Internet Radio (Tuneln)	•
Spotify Connect, Deezer, TIDAL, Napster, Soundcloud *	• / • / • / • / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna / dual band)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio	•
FM / AM Tuner	• / •
Bluetooth	•
<b>HDMI</b>	
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •
eARC (Enhanced Audio Return Channel)	•
Dolby Vision compatible / Hybrid Log Gamma (HLG)	• / •
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Video processing and -scaling	1080p, 4K 60/50Hz

\* This feature is not available in all countries.

INPUTS/OUTPUTS			
VIDEO			
Composite In / Out		3+1 / 2	
Component In / Out		3 / 1	
HDMI In / Out		7+1 / 3 (2 main + 1 zone)	
AUDIO			
Analogue In / Out		5+1 / 0	
Digital Optical In		2	
Digital Coaxial In		2	
Multichannel Pre Out		● (11.2 with 11.2 processing)	
Zone audio preout		2	
Subwoofer Out		2	
7.1 Multichannel input		●	
SPECIFICATIONS			
Number of poweramps		9	
Power Output per channel			
6 ohm, 1 kHz, 1%, 1ch Drive		200 W	
6 ohm, 1 kHz, 0.7%, 2ch Drive		165 W	
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive		125 W	
Audio Signal to Noise Ratio		102 dB	
GENERAL			
Available colours: Black / Silver-Gold		● / ●	
System Remote Control		RC036SR	
Power Consumption in W		710	
Power Consumption No-Sound (ECO ...on/off) in W		65 / 110	
Standby Consumption in W		0.2 (with CEC 0.5)	
Maximum Dimensions (W x D x H) in mm		440 x 411 x 185	
Weight in kg		14.2	
EAN			
EU	SR7013/N1B	4951035065983	Black
	SR7013/N1SG	4951035066027	Silvergold
UK	SR7013/T1B	4951035066546	Black
	SR7013/T1SG	4951035066553	Silvergold



The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/third-party-licenses](http://www.spotify.com/connect/third-party-licenses). Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

\* All specs can be subject to change.

**ONLINE HI-FI**  
AUDIO EXCELLENCE

www.onlinehifi.co.nz  
Email: info@bwspeakers.co.nz  
Freephone: 0800 255 800